

Wash FX Hex ILS

HIGHLIGHTS

- Multi-purpose effect light functions as a chase effect, blinder, or wash light
- ILS compatibility for use in the ILS ecosystem (D-Fi™ USB sold separately)
- D-Fi USB compatibility for wireless Master/Slave or DMX control
- Generate a broad spectrum of colors and achieve natural-looking color temperatures with Hex color LEDs
- Advanced master/slave feature allows you to mirror effect between units
- Use as a regular wash light or eye-candy effect with 6 chasing zones
- Multiple control options include stand-alone, DMX, IR, or master/slave
- Compatible with the IRC6 wireless remote for wireless triggering
- Fits best in the CHS-40 VIP Gear Bag



SPECIFICATIONS

- DMX Channels : 3, 6, 11 or 40
- DMX Connectors : 3-pin XLR
- Light Source : 18 LEDs (hex-color RGBAW+UV) 10 W, 2.5 A, 50,000 hours life expectancy
- Strobe Rate : 0 to 20 Hz
- Beam Angle : 44°
- Field Angle : 77°
- Illuminance : 3,204 lux @ 2 m
- Power Linking : 6 units @ 120 V; 11 units @ 230 V
- Input Voltage : 100 to 240 VAC, 50/60 Hz (auto-ranging)
- Power and Current : 160 W, 1.3 A @ 120 V, 60 Hz
- Weight : 6.8 lbs. (3.1 kg)
- Size : 11. x 9.5 x 7.1 in (280 x 240 x 180 mm)
- Approvals : CE, RoHS, UKCA
- Wavelength (UV) : 395 to 405 nm
- Power and Current : 160 W, 1.3 A @ 120 V, 60 Hz
- Power and Current : 160 W, 1.3 A @ 120 V, 60 Hz
- Optional Controllers : IRC-6, ILS Command

WHAT'S INCLUDED

- Wash FX Hex ILS
- Power cable
- Quick Reference Guide